

Study of Tomlinson-Harashima Precoding Strategies for Physical-Layer Security in Wireless Networks

Xiaotao Lu, Rodrigo C. de Lamare and Keke Zu

Abstract—In this paper, we propose novel non-linear precoders for the downlink of a multi-user MIMO system with the existence of multiple eavesdroppers. The proposed non-linear precoders are designed to improve the physical-layer secrecy rate. Specifically, we combine the non-linear successive optimization Tomlinson-Harashima precoding (SO-THP) with generalized matrix inversion (GMI) technique to maximize the physical-layer secrecy rate. For the purpose of comparison, we examine different traditional precoders with the proposed algorithm in terms of secrecy rate as well as BER performance. We also investigate simplified generalized matrix inversion (S-GMI) and lattice-reduction (LR) techniques in order to efficiently compute the parameters of the precoders. We further conduct computational complexity and secrecy rate analysis of the proposed and existing algorithms. In addition, in the scenario without knowledge of channel state information (CSI) to the eavesdroppers, a strategy of injecting artificial noise (AN) prior to the transmission is employed to enhance the physical-layer secrecy rate. Simulation results show that the proposed non-linear precoders outperform existing precoders in terms of BER and secrecy rate performance.

Index Terms—Physical-layer security, precoding algorithms, successive optimization, secrecy rate analysis.

I. INTRODUCTION

Data security in wireless systems has been traditionally dominated by encryption methods such as Data Encryption Standard (DES) and Advanced Encryption Standard (AES) [1]. However, these existing encryption algorithms suffer from high complexity and high latency. Besides, development in computing power also brings great challenges to existing encryption techniques. Therefore, are capable of achieving secure transmission under high computing power scenario with low complexity have become an important research topic.

From the viewpoint of information theory, Shannon established the theorem of cryptography in his seminal paper [3]. Wyner has subsequently posed the Alice-Bob-Eve problem and described the wire-tap transmission system [3]. Furthermore, the system discussed in [3] suggests that physical layer security can be achieved in wireless networks. Later on, another study reported in [4] proved that secrecy transmission is achievable even under the situation that the eavesdropper has a better channel than the desired user in a statistical sense. Furthermore, the secrecy capacity for different kinds of channels, such as Gaussian wire-tap channel and multi-input

multi-output (MIMO) wire-tap channel have been studied in [5], [6]. In some later works [7], [8], [9], it has been found that the secrecy of the transmission can be further enhanced by adding artificial noise to the system.

A. Prior and Related Work

In recent years, precoding techniques, which rely on knowledge of channel state information (CSI), have been widely studied in the downlink of multiuser MIMO (MU-MIMO) and cooperative systems [41], [42], [43], [44], [45], [46], [11], [47], [48], [49], [50], [51], [52], [53], [54], [55], [56], [57], [58], [59], [60], [15], [61], [62], [63], [64], [17], [65], [66], [67], [68], [69], [70], [71], [72], [73], [78], [75], [76], [77], [78], [79], [80], [81], [82], [83], [20], [21], [22]. Linear precoding techniques such as zero-forcing (ZF), minimum mean-square error (MMSE) and block diagonalization (BD) have been introduced and studied in [23], [24], [25]. Furthermore, non-linear precoding techniques like Tomlinson-Harashima precoding (THP) [26], vector perturbation (VP) precoding [27] have also been reported and investigated. In the previous mentioned works, the implementation of linear or non-linear precoding techniques at the transmitter are considered with perfect knowledge of CSI to the users. In the scenario without knowledge of CSI to the eavesdroppers, one technique which is effective in improving the secrecy rate of the downlink of MU-MIMO systems is the application of artificial noise (AN) at the transmitter [7]. Several criteria or strategies applying AN to wireless systems have been introduced in [28], [29]. In particular, the approaches reported in [8] have been applied to the downlink of MU-MIMO systems. Apart from the studies in precoding techniques there are also some works that introduce lattice-reduction (LR) strategies [30], [31]. The LR strategies are also implemented prior to the transmission and it has been proved that the LR aided system can achieve full diversity in the downlink of MU-MIMO systems.

B. Motivation and Contributions

Prior work on precoding for physical-layer security systems has been heavily based on [7], [8], which can effectively improve the secrecy rate of wireless systems. However, it is well known in the wireless communications literature that non-linear precoding techniques can outperform linear approaches. In particular, non-linear precoding techniques require lower transmit power than linear schemes and can achieve higher sum-rates. However, work on non-linear precoding for physical-layer security in wireless systems is extremely limited even though there is potential to significantly

Xiaotao Lu is with the Communications Research Group, Department of Electronics, University of York, YO10 5DD York, U.K., R. C. de Lamare is with CETUC, PUC-Rio, Brazil and with the Communications Research Group, Department of Electronics, University of York, YO10 5DD York, U.K. and Keke Zu is with Ericsson Research, Sweden, e-mails: xtl503@york.ac.uk; rodrigo.delamare@york.ac.uk; zukeke@gmail.com.

improve the secrecy rate of wireless systems. The motivation for this work is to develop and study non-linear precoding algorithms for MU-MIMO systems that can achieve a secrecy rate higher than that obtained by linear precoders as well as a lower transmit power requirement and an improved bit error rate (BER) performance.

In our work, we develop and study a successive optimization Tomlinson-Harashima precoding (SO-THP) precoding algorithms based on the generalized matrix inversion approach reported in [25]. Specifically, the proposed non-linear precoders exploit both successive interference cancellation, lattice-reduction and block diagonalization, which can impose orthogonality between the channels of the desired users [84], [85], [86], [87], [88], [89], [90], [91], [105], [93], [94], [95], [96], [97], [98], [99], [100], [101], [102], [103], [104], [105], [106], [107], [108], [109], [110], [111], [112], [116], [114], [115], [116], [117], [118], [119], [120], [121], [122], [123], [124], [125], [126], [127], [128], [129], [130], [131], [132], [133], [134], [135]. This combined approach has not been considered previously in the literature and has the potential of achieving a higher secrecy rate than existing non-linear and linear precoding algorithms as well as an improved BER performance as compared to prior art. The major contributions in our paper are summarized as follows:

- A novel non-linear precoding technique, namely, SO-THP+GMI is proposed for the downlink of MU-MIMO networks in the presence of multiple eavesdroppers.
- The proposed SO-THP+GMI algorithm combines the SO-THP precoding with the GMI technique to achieve a higher secrecy rate.
- The proposed SO-THP+GMI precoding algorithm is extended to a S-GMI version which aims to reduce computational complexity of the SO-THP+GMI algorithm.
- An LR strategy is combined with the aforementioned S-GMI version proposed algorithm and this so-called LR-aided version algorithm achieves full receive diversity.
- An analysis of the secrecy rate achieved by the proposed non-linear precoding algorithms is carried out along with an assessment of their computational complexity cost.

The rest of this paper is organized as follows. We begin in Section II by introducing the system model and the performance metrics. A brief review of the standard SO-THP algorithm is included in Section III. In Section IV, we present the details of proposed SO-THP+GMI, SO-THP+S-GMI and LR-SO-THP+S-GMI precoding algorithms. Next in Section V, the analysis of secrecy rate and the computational complexity of the precoding algorithms are carried out. In Section VI, numerical evaluation is conducted to show the advantage of proposed precoding algorithms. Finally, some concluding remarks are given in Section VII.

C. Notation

Bold uppercase letters $\mathbf{A} \in \mathbb{C}^{M \times N}$ denote matrices with size $M \times N$ and bold lowercase letters $\mathbf{a} \in \mathbb{C}^{M \times 1}$ denote column vectors with length M . Conjugate, transpose, and conjugate transpose are represented by $(\cdot)^*$, $(\cdot)^T$ and $(\cdot)^H$ respectively; \mathbf{I}_M is the identity matrix of size $M \times M$;

$\text{diag}\{\mathbf{a}\}$ denotes a diagonal matrix with the elements of the vector \mathbf{a} along its diagonal; $\mathcal{CN}(0, \sigma_n^2)$ represents complex Gaussian random variables with *i.i.d* entries with zero mean and σ_n^2 variance.

II. SYSTEM MODEL AND PERFORMANCE METRICS

In this section we introduce the system model of the downlink of the MU-MIMO network under consideration. The performance metrics used in the assessment of the proposed and existing techniques are also described.

A. System Model




Fig. 1. System model of a MU-MIMO system with T users and K eavesdroppers

Consider a MU-MIMO downlink wireless network consisting of one transmitter or Alice at the access point, T users or Bob and K eavesdroppers or Eve at the receiver side as shown in Fig. 1. The transmitter is equipped with N_t antennas. Each user and each eavesdropper node are equipped with N_r and N_k receive antennas, respectively. In this system we assume that the eavesdroppers do not jam the transmission and the channel from the transmitter to each user or eavesdropper follows a flat-fading channel model. The quantities $\mathbf{H}_r \in \mathbb{C}^{N_r \times N_t}$ and $\mathbf{H}_k \in \mathbb{C}^{N_k \times N_t}$ denote the channel matrix of the i th user and k th eavesdropper, respectively. Following [37], the number of antennas should satisfy $N_t^{\text{total}} \geq T \times N_r$. During the transmission, $N_t = M \times N_r$ antennas at the transmitter are activated to perform the precoding procedure. In other words, the precoding matrix is assumed here for convenience to be always a square matrix.

We use the vector $\mathbf{s}_r \in \mathbb{C}^{N_r \times 1}$ to represent the data symbols to be transmitted to user r . An artificial noise (AN) can be injected before the data transmission to enhance the physical-layer secrecy. We use the vector $\mathbf{s}'_r \in \mathbb{C}^{m \times 1}$ with $m \leq (N_t^{\text{total}} - T \times N_r)$ to denote the independently generated jamming signal. Assume the transmit power of user r is E_r ,

and $0 < \rho < 1$ is the power fraction devoted to the user. Then, the power of user and jamming signal can be respectively expressed as $E[s_r^H s_r] = \rho E_r$ and $E[s_r'^H s_r'] = (1 - \rho) E_r$. Finally the signal after precoding can be expressed as

$$\mathbf{x}_r = \mathbf{P}_r \mathbf{s}_r + \mathbf{P}'_r \mathbf{s}'_r, \quad (1)$$

where the quantities $\mathbf{P}_r \in \mathbb{C}^{N_t \times N_r}$ and $\mathbf{P}'_r \in \mathbb{C}^{N_t \times m}$ are the corresponding precoding matrices. Here we take zero-forcing precoding as an instance. Given the total channel matrix $\mathbf{H} = [\mathbf{H}_1^T \ \mathbf{H}_2^T \ \dots \ \mathbf{H}_r^T \ \dots \ \mathbf{H}_M^T]^T$, the total precoding matrix can be obtained as $\mathbf{P}^{\text{ZF}} = \mathbf{H}^H (\mathbf{H} \mathbf{H}^H)^{-1}$. The precoding matrix \mathbf{P}^{ZF} can be expanded to $\mathbf{P}^{\text{ZF}} = [\mathbf{P}_1 \ \mathbf{P}_2 \ \dots \ \mathbf{P}_r \ \dots \ \mathbf{P}_M]$. Simultaneously, the precoding matrix \mathbf{P}'_r can be generated from the null space of the r th user channel \mathbf{H}_r by singular value decomposition (SVD) [8]. Note that other precoding strategies [13], [18], [15], [16], [17], [?] and MMSE filters can also be considered [38], [39], [40], [41], [118], [42], [43], [44], [45], [100], [111], [46], [133], [47], [48], [131], [49]. As a result, we have $\mathbf{H}_r \mathbf{P}'_r = \mathbf{0}$, which means the jamming signal does not interfere the user's signal. The received data for each user or eavesdropper can be described by

$$\mathbf{y}_r = \beta_r^{-1} (\mathbf{H}_r \mathbf{P}_r \mathbf{s}_r + \mathbf{H}_r \mathbf{P}'_r \mathbf{s}'_r + \mathbf{H}_r \sum_{j=1, j \neq r}^T \mathbf{P}_j \mathbf{s}_j + \mathbf{n}_r), \quad (2)$$

where $\beta_r = \sqrt{\frac{E_r}{\|\mathbf{P}_r\| + \|\mathbf{P}'_r\|}}$ is used to ensure that the transmit power after precoding remains the same as the original transmit power E_r for user r .

B. Secrecy Rate and Other Relevant Metrics

In this subsection, we describe the main performance metrics used in the literature to assess the performance of precoding algorithms.

1) *Secrecy rate and secrecy capacity*: According to [3], the level of secrecy is measured by the uncertainty of Eve about the message R_e which is called the equivocation rate. With the total power equal to E_s , the maximum secrecy capacity C_s for the MIMO system without AN is expressed as [6]

$$C_s = \max_{\mathbf{Q}_s \geq 0, \text{Tr}(\mathbf{Q}_s) = E_s} \log(\det(\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H)) - \log(\det(\mathbf{I} + \mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H)), \quad (3)$$

where the quantity \mathbf{Q}_s is the covariance matrix associated with the signal after precoding. However, the channels between the transmitter and the eavesdroppers are usually not perfectly known in reality. This situation is known as the imperfect channel state information (CSI) case in [7], which we will address in our studies.

2) *Computational complexity*: According to the study in [37], non-linear precoding techniques can approach the maximum channel capacity with high computational complexity. High complexity of the algorithm directly leads to a high cost of power consumption. In our research, however, novel non-linear precoding algorithms with reduced complexity are developed.

3) *BER performance*: Ideally, we would like the users to experience reliable communication and the eavesdroppers to have a very high BER (virtually no reliability when communicating). The algorithm is supposed to achieve high diversity for the MIMO system.

III. REVIEW OF THE SO-THP ALGORITHM

In this section, a brief review of the conventional successive optimization THP (SO-THP) in [23] is given. The general structure of the SO-THP algorithm is illustrated in Fig. 2 and its main implementation steps are introduced in the following.




Fig. 2. Centralized SO-THP structure

In Fig. 2, a modulo operation $M(\cdot)$ which is defined in [50] is employed to fulfill the SO-THP algorithm. Based on [37], THP can be equivalently implemented in a successive block diagonalization manner. In particular, the precoding matrix is given by

$$\mathbf{P}_r^{\text{BD}} = \tilde{\mathbf{V}}_r^{(0)} \mathbf{V}_{\text{eff}}, \quad (4)$$

where $\tilde{\mathbf{V}}_r^{(0)} \in \mathbb{C}^{N_t \times N_r}$ is the nulling matrix of r th user's channel, \mathbf{V}_{eff} is a unitary matrix of the corresponding effective channel and the demodulation matrix of the r th user is chosen as $\mathbf{D}_r = \mathbf{U}_{\text{eff}}^H$, where $\mathbf{U}_{\text{eff}}^H$ is also obtained from the effective channel. Given a channel matrix $\tilde{\mathbf{H}}_r = [\tilde{\mathbf{H}}_1^T \ \tilde{\mathbf{H}}_2^T \ \dots \ \tilde{\mathbf{H}}_{r-1}^T \ \tilde{\mathbf{H}}_{r+1}^T \ \dots \ \tilde{\mathbf{H}}_T^T]^T$, $\tilde{\mathbf{V}}_r^{(0)}$ can be obtained by the SVD operation $\tilde{\mathbf{H}}_r = \tilde{\mathbf{U}}_r \tilde{\Sigma}_r [\tilde{\mathbf{V}}_r^{(1)} \tilde{\mathbf{V}}_r^{(0)}]^H$. Based on $\tilde{\mathbf{V}}_r^{(0)}$, an effective channel can be calculated and with second SVD operation $\mathbf{H}_{\text{eff}} = \mathbf{H}_r \tilde{\mathbf{V}}_r^{(0)} = \mathbf{U}_{\text{eff}} \Sigma_{\text{eff}} \mathbf{V}_{\text{eff}}^H$ we are capable of getting \mathbf{V}_{eff} and $\mathbf{U}_{\text{eff}}^H$. For each iteration, the SO-THP algorithm selects the user with maximum capacity from the remaining users and process it first. The selection criterion is described as

$$\arg \min_r (C_{\max, r} - C_r); \quad (5)$$

where $C_{\max, r}$ denotes the maximum capacity of the r th user and C_r is the capacity considering the interference from the other users. If we assume there is no interference from other users and the capacity can be achieved by the SVD procedure, we have

$$\mathbf{H}_r = \mathbf{U}_r \Sigma_r [\mathbf{V}_r^{(1)} \mathbf{V}_r^{(0)}]^H, \quad (6)$$

$$C_{\max, r} = \log_2 \det \left(\mathbf{I} + \mathbf{H}_r \mathbf{V}_r^{(1)} \mathbf{V}_r^{(1)H} \mathbf{H}_r^H \right). \quad (7)$$

In the scenario considering the interference from the other users, the BD decomposition is implemented on the channels of the remaining users in each iteration:

$$C_r = \log_2 \det \left(\mathbf{I} + \mathbf{H}_r \mathbf{P}_r \mathbf{P}_r^H \mathbf{H}_r^H \right); \quad (8)$$

Therefore, the filters for the SO-THP algorithm can be obtained as

$$\mathbf{F} = (\mathbf{P}_1^{\text{BD}} \cdots \mathbf{P}_T^{\text{BD}}), \quad (9)$$

$$\mathbf{D} = \begin{pmatrix} \mathbf{U}_{\text{eff1}}^H & & \\ & \ddots & \\ & & \mathbf{U}_{\text{effT}}^H \end{pmatrix}, \quad (10)$$

$$\mathbf{B} = \text{lower triangular}(\mathbf{D}\mathbf{H}\mathbf{F} \bullet \text{diag}([\mathbf{D}\mathbf{H}\mathbf{F}]_{ii}^{-1})). \quad (11)$$

It is worth noting that \mathbf{F} in (9), \mathbf{D} in (10) are calculated in the reordered way according to equation(5), and the scaling matrix $\mathbf{G} = \text{diag}([\mathbf{D}\mathbf{H}\mathbf{F}]_{ii}^{-1})$.

IV. PROPOSED PRECODING ALGORITHMS

In this section, we present three non-linear precoding algorithms SO-THP+GMI, SO-THP+S-GMI and LR-SO-THP+S-GMI for the downlink of MU-MIMO systems, and a selection criterion based on capacity is devised for these algorithms. We then derive filters for the three proposed precoding techniques, which are computationally simpler than SO-THP.

According to [37], the conventional SO-THP algorithm has the advantage of improving the BER and the sum rate performances, however, the complexity of this algorithm is high due to the successive optimization procedure and the multiple SVD operations. In [51], an approach called generalized MMSE channel inversion (GMI) is developed to overcome the noise enhancement drawback of BD caused by its completely focus on the suppression of multi-user interference. Later in [53], it has been shown that the complete suppression of multi-user interference is not necessary and residual interference is so small that cannot affect the sum-rate performance. This approach is called simplified GMI (S-GMI). The proposed algorithms are inspired by dirty paper coding (DPC) [?] and other non-linear precoding techniques [37], [52], [63] which have been investigated for the downlink of MU-MIMO systems.

A. SO-THP+GMI Algorithm

The proposed SO-THP+GMI algorithm mainly focuses on achieving high secrecy rate performance with lower complexity than the conventional SO-THP algorithm. In the conventional SO-THP algorithm the precoding matrix as well as the receive filters are obtained with (4) using the BD algorithm without considering noise enhancement. In [51], the GMI scheme uses the QR decomposition to decompose the MMSE channel inversion $\bar{\mathbf{H}} \in \mathbb{C}^{N_t \times TN_r}$ as expressed by

$$\bar{\mathbf{H}} = (\mathbf{H}^H \mathbf{H} + \alpha \mathbf{I})^{-1} \mathbf{H}^H, \quad (12)$$

$$\bar{\mathbf{H}}_r = [\bar{\mathbf{Q}}_r^{(0)} \quad \bar{\mathbf{Q}}_r^{(1)}] \bar{\mathbf{R}}_r \quad \text{for } r = 1, \dots, T, \quad (13)$$

where $\bar{\mathbf{H}}_r \in \mathbb{C}^{N_t \times N_r}$, $\bar{\mathbf{Q}}_r^{(0)} \in \mathbb{C}^{N_t \times N_t}$ is an orthogonal matrix, $\bar{\mathbf{R}}_r \in \mathbb{C}^{N_t \times N_r}$ is an upper triangular matrix. In (12), the noise is taken into account. As a result, the generation of the precoding matrix will mitigate the noise enhancement. When the GMI generated precoding matrix is used to calculate the channel capacity with (8), the reduced noise contributes to

the increase of secrecy rate. Also with (13), the QR decomposition reduces the computational complexity as compared with the conventional SO-THP algorithm implementing the SVD decomposition. To completely mitigate the interference, a transmit combining matrix \mathbf{T}_r given in [51] is applied to $\bar{\mathbf{Q}}_r^{(0)}$. Once we have $\bar{\mathbf{Q}}_r^{(0)}$ and \mathbf{T}_r , we can write the relation

$$\mathbf{H}_r \bar{\mathbf{Q}}_r^{(0)} \mathbf{T}_r = \bar{\mathbf{U}}_r \bar{\Sigma}_r \bar{\mathbf{V}}_r^H, \quad (14)$$

Then the precoding matrix as well as the receive filter for the GMI scheme are given by

$$\mathbf{P}_{\text{GMI}} = [\bar{\mathbf{Q}}_1^{(0)} \mathbf{T}_1 \bar{\mathbf{V}}_1 \quad \bar{\mathbf{Q}}_2^{(0)} \mathbf{T}_2 \bar{\mathbf{V}}_2 \quad \cdots \quad \bar{\mathbf{Q}}_T^{(0)} \mathbf{T}_T \bar{\mathbf{V}}_T], \quad (15)$$

$$\mathbf{M}_{\text{GMI}} = \text{diag}\{\bar{\mathbf{U}}_1^H \quad \bar{\mathbf{U}}_2^H \quad \cdots \quad \bar{\mathbf{U}}_T^H\}, \quad (16)$$

where $\mathbf{P}_{\text{GMI}} \in \mathbb{C}^{N_t \times N_t}$ and $\mathbf{M}_{\text{GMI}} \in \mathbb{C}^{N_t \times N_t}$. The details of the proposed SO-THP+GMI algorithm to obtain the precoding and receive filter matrices are given in the table of Algorithm 1.

Algorithm 1 Proposed SO-THP+GMI Precoding

```

1: for  $r = 1 : T$  do
2:    $\mathbf{G}_r = \mathbf{H}_r$ ;
3:    $\mathbf{G}_r = \mathbf{U}_r \bar{\Sigma}_r [\mathbf{V}_r^{(1)} \mathbf{V}_r^{(0)}]^H$ ;
4:    $\mathbf{F}_r = \mathbf{V}_r^{(1)}$ ;
5:    $C_{\max, r} = \log_2 \det(\mathbf{I} + \mathbf{R}_{k, r}^{-1} \mathbf{G}_r \mathbf{F}_r \mathbf{F}_r^H \mathbf{G}_r^H)$ ;
6: end for
7:  $\mathbf{M} = \mathbf{H}$ ;
8: loop
9:   while  $r = T : 1$  do
10:    for  $n = 1 : r$  do
11:       $\mathbf{G} = (\mathbf{M}^H \mathbf{M} + \alpha \mathbf{I})^{-1} \mathbf{M}^H$ 
12:       $\mathbf{G}_n = [\bar{\mathbf{Q}}_r^{(0)} \quad \bar{\mathbf{Q}}_r^{(1)}] \bar{\mathbf{R}}_n$ 
13:       $\mathbf{M}_n \bar{\mathbf{Q}}_r^{(0)} \mathbf{T}_r = \bar{\mathbf{U}}_n \bar{\Sigma}_n \bar{\mathbf{V}}_n^H$ 
14:       $\mathbf{P}_n = \bar{\mathbf{Q}}_n^{(0)} \mathbf{T}_r \bar{\mathbf{V}}_n^{(1)}$ 
15:    end for
16:    for  $j = 1 : r$  do
17:       $C_j = \log_2 \det(\mathbf{I} + \mathbf{R}_{k, j}^{-1} \mathbf{M}_j \mathbf{P}_j \mathbf{P}_j^H \mathbf{M}_j^H)$ ;
18:    end for
19:     $a_r = \arg \min_j (C_{\max, j} - C_j)$ ;
20:     $\mathbf{F}_r = \mathbf{P}_{a_r}$ ;
21:     $\mathbf{D}_r = \bar{\mathbf{U}}_{a_r}^H$ ;
22:     $\mathbf{M} = [\mathbf{H}_1^T \cdots \mathbf{H}_{a_r-1}^T \mathbf{H}_{a_r+1}^T \cdots \mathbf{H}_T^T]^T$ 
23:  end while
24: end loop
25:  $\mathbf{F} = (\mathbf{F}_1 \cdots \mathbf{F}_T)$ ;
26:  $\mathbf{D} = \begin{pmatrix} \mathbf{D}_1 & & \\ & \ddots & \\ & & \mathbf{D}_T \end{pmatrix}$ 
27:  $\mathbf{B} = \text{lower triangular}(\mathbf{D}\mathbf{H}\mathbf{F} \bullet \text{diag}([\mathbf{D}\mathbf{H}\mathbf{F}]_{rr}^{-1}))$ 

```

B. SO-THP+S-GMI Algorithm

Further development on SO-THP+GMI with complexity reduction leads to a novel SO-THP+S-GMI algorithm. A simplified GMI (S-GMI) has been developed in [53] as an

improvement of the original RBD precoding in [23]. This is known as S-GMI. In (14), a transmit combining matrix is applied to achieve complete interference cancelation between different users. In this case, the interference will not be completely mitigated, resulting in a slight decrease of the sum-rate even though the complexity will have a significant reduction [53]. Here, we incorporate the S-GMI technique into an SO-THP scheme and devise the SO-THP+S-GMI algorithm. The transmit and receive filters of the proposed SO-THP+S-GMI algorithm are described by

$$\mathbf{H}_r \bar{\mathbf{Q}}_r^{(0)} = \tilde{\mathbf{U}}_r \tilde{\Sigma}_r \tilde{\mathbf{V}}_r^H, \quad (17)$$

$$\mathbf{P}_{\text{S-GMI}} = [\bar{\mathbf{Q}}_1^{(0)} \tilde{\mathbf{V}}_1 \quad \bar{\mathbf{Q}}_2^{(0)} \tilde{\mathbf{V}}_2 \quad \cdots \quad \bar{\mathbf{Q}}_T^{(0)} \tilde{\mathbf{V}}_T], \quad (18)$$

$$\mathbf{M}_{\text{S-GMI}} = \text{diag}\{\tilde{\mathbf{U}}_1^H \quad \tilde{\mathbf{U}}_2^H \quad \cdots \quad \tilde{\mathbf{U}}_T^H\}, \quad (19)$$

where $\mathbf{P}_{\text{S-GMI}} \in \mathbb{C}^{N_t \times N_t}$, $\mathbf{M}_{\text{S-GMI}} \in \mathbb{C}^{N_t \times N_t}$.

With reduced computational complexity, the SO-THP+S-GMI algorithm is capable of achieving better secrecy rate performance especially at lower SNR. The detailed S-GMI procedure implemented in the proposed SO-THP+S-GMI algorithm is shown in Algorithm 2. Cooperated with Algorithm 1, the precoding and receive filter matrices can be obtained.

Algorithm 2 S-GMI Precoding

```

1: for  $n = 1 : r$  do
2:    $\mathbf{G} = (\mathbf{M}^H \mathbf{M} + \alpha \mathbf{I})^{-1} \mathbf{M}^H$ 
3:    $\mathbf{G}_n = [\bar{\mathbf{Q}}_n^{(0)} \quad \bar{\mathbf{Q}}_n^{(1)}] \bar{\mathbf{R}}_n$ 
4:    $\mathbf{M}_n \bar{\mathbf{Q}}_n^{(0)} = \tilde{\mathbf{U}}_n \tilde{\Sigma}_n \tilde{\mathbf{V}}_n^H$ 
5:    $\mathbf{P}_n = \bar{\mathbf{Q}}_n^{(0)} \tilde{\mathbf{V}}_n^{(1)}$ 
6: end for

```

C. LR-SO-THP+S-GMI Algorithm

The development in linear algebra contribute to the lattice reduction technique application in wireless networks. According to study in [30], a basis change may lead to improved performance as corroborated by lattice reduction techniques. The more correlated the columns of channel \mathbf{H} , the more significant the improvements will be. To achieve full diversity of the system, with complex lattice reduction algorithm (CLR) [55], the LR transformed channel for the r th user is obtained as

$$\mathbf{H}_{red,r}^H = \mathbf{H}_r^H \mathbf{L}_r \quad (20)$$

where $\mathbf{H}_{red,r} \in \mathbb{C}^{N_r \times N_t}$ is the transposed reduced channel matrix. The quantity $\mathbf{L}_r \in \mathbb{C}^{N_r \times N_r}$ is the transform matrix generated by the CLR algorithm. Note that the transmit power constraint is satisfied since \mathbf{M}_r is a unimodular matrix.

Compared to the conventional SO-THP algorithm, the lattice reduced channel matrix $\mathbf{H}_{red,n}$ is employed in the conventional S-GMI algorithm. The details of the LR aided S-GMI Procedure are given in Algorithm 3. Cooperated with Algorithm 1, we can complete the calculation of precoding and receive filter matrices.

Algorithm 3 Lattice-Reduction aided S-GMI Procedure

```

1: for  $n = 1 : r$  do
2:    $\mathbf{G} = (\mathbf{H}^H \mathbf{H} + \alpha \mathbf{I})^{-1} \mathbf{H}^H$ 
3:    $[\mathbf{H}_{red,n}^H \quad \bar{\mathbf{Q}}_n^{(0)}] = \text{CLLL}(\mathbf{G}_n^H)$ 
4:    $\mathbf{M}_n = \mathbf{H}_{red,n}$ 
5:    $\mathbf{M}_n \bar{\mathbf{Q}}_n^{(0)} = \tilde{\mathbf{U}}_n \tilde{\Sigma}_n \tilde{\mathbf{V}}_n^H$ 
6:    $\mathbf{P}_n = \bar{\mathbf{Q}}_n^{(0)} \tilde{\mathbf{V}}_n^{(1)}$ 
7: end for

```

V. ANALYSIS OF THE ALGORITHMS

In this section, we develop an analysis of the secrecy rate of the proposed precoding algorithms along with a comparison of the computational complexity between the proposed and existing techniques.

A. Computational Complexity Analysis

TABLE I
COMPUTATIONAL COMPLEXITY OF THE PROPOSED SO-THP+GMI ALGORITHM

Steps	Operations	Flops	Case (2, 2, 2) × 6
1	$\mathbf{G}_r = \mathbf{U}_r \Sigma_r [\mathbf{V}_r^{(1)} \mathbf{V}_r^{(0)}]^H$	$32R(N_t N_r^2 + N_r^3)$	3072
2	$\bar{\mathbf{G}} = \mathbf{G} = (\mathbf{H}^H \mathbf{H} + \alpha \mathbf{I})^{-1} \mathbf{H}^H$	$(2N_t^3 - 2N_t^2) + N_t + 16N_R N_t^2$	3822
3	$\bar{\mathbf{G}}_n = \bar{\mathbf{Q}}_n \bar{\mathbf{R}}_n$	$\sum_{r=1}^R 16r(N_t^2 N_r + N_t N_r^2 + \frac{1}{3} N_r^3)$	9472
4	$\mathbf{H}_{eff,n} = \mathbf{H}_n \bar{\mathbf{Q}}_n \mathbf{T}_n$	$\sum_{r=1}^R 16r N_R N_t^2$	20736
5	$\mathbf{H}_{eff,n} = \mathbf{U}_n^{(4)} \Sigma_n^{(4)} \mathbf{V}_n^{(4)H}$	$\sum_{r=1}^R 64r(\frac{9}{8} N_r^3 + N_t N_r^2 + \frac{1}{2} N_t^2 N_r)$	26496
6	$\mathbf{B} = \text{lower triangular} (\mathbf{DHF} \bullet \text{diag}([\mathbf{DHF}]_{rr}^{-1}))$	$16N_R N_t^2$	3456
			total 67054

According to [55], it can be calculated that the cost of the QR in FLOPs is 22.4% lower than BD. The results shown in Table I indicate that the complexity is reduced by about 22.4% by the proposed SO-THP+GMI compared with the conventional SO-THP calculated in the same way. Based on the proposed SO-THP+GMI algorithm, further complexity reduction can be achieved by SO-THP+S-GMI and the complexity is about 34.4% less than that of the conventional SO-THP algorithm.

Fig. 3 shows the required FLOPS of the proposed and existing precoding algorithms. Linear precoding gives lower computational complexity but the BER performance is worse than non-linear ones. The three proposed algorithms show an advantage over the conventional SO-THP algorithm in terms of complexity. Among all the three proposed algorithms, SO-THP+S-GMI has the lowest complexity followed by LR-SO-THP+S-GMI. SO-THP+GMI requires the highest complexity.




Fig. 3. Computational complexity in FLOPs for MU-MIMO systems

B. Secrecy rate Analysis

Theorem 1: In full-rank MU-MIMO systems with perfect knowledge of CSI, the proposed algorithms are capable of achieving a high secrecy rate and in the high-SNR regime (i.e., $E_s \rightarrow \infty$) the secrecy rate will converge to $C_{sec}^{E_s \rightarrow \infty}$ which is given as (21),

$$C_{sec}^{E_s \rightarrow \infty} = \log \left(\det \left((\mathbf{H}_{ea} \mathbf{H}_{ea}^H)^{-1} (\mathbf{H}_{ba} \mathbf{H}_{ba}^H) \right) \right) \quad (21)$$

Proof: Under the conditions

$$\mathbf{H}_{ba}^H \mathbf{H}_{ba} \succeq \mathbf{H}_{ea}^H \mathbf{H}_{ea} \quad (22)$$

$$\text{rank}(\mathbf{H}_{ba}) = \text{rank}(\mathbf{H}_{ea}) \quad (23)$$

and based on (3) we can have the secrecy capacity expressed as (24). If $\Gamma(\mathbf{P}) = (\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} (\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)$, (24) can be converted to (25).

In (25), (26) and (27), \mathbf{P} is the precoding matrix derived from the legitimate users' channel. With $\mathbf{Q}_s = E[\mathbf{x}_s \mathbf{x}_s^H] = E[\mathbf{P} \mathbf{s} \mathbf{s}^H \mathbf{P}^H]$, $E[\mathbf{s} \mathbf{s}^H] = E_s$ and $\mathbf{P} \mathbf{P}^H = \mathbf{I}$, we can have,

$$E[(\mathbf{P} \mathbf{P}^H)^{-1} \mathbf{Q}_s] = E_s \quad (28)$$

Then

$$E[(\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H] = E_s \quad (29)$$

$$E[(\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} \mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H] = E_s \quad (30)$$

In (25), the expectation value is given as (31). Substituting (29) into (31) the formula can be expressed as (33).

According to (33), in the high-SNR regime and when $\text{SNR} \rightarrow \infty$, $E_s \rightarrow \infty$, $\mathbf{S} \mathbf{A} \rightarrow \mathbf{I}$. Then, the secrecy rate expressed in (25) will result in (34). To satisfy the power constrain, we always have $E[\mathbf{P} \mathbf{P}^H] = \mathbf{I}$, then the secrecy rate C_{sec} will converge to a constant, that is,

$$C_{sec}^{E_s \rightarrow \infty} = \log \left(\det(\mathbf{H}_{ea} \mathbf{H}_{ea}^H)^{-1} (\mathbf{H}_{ba} \mathbf{H}_{ba}^H) \right) \quad (35)$$

This completes the proof. \blacksquare

In the following, the percentage of the injected artificial noise power is set to 40% of the total transmit power. When AN is added during the transmission, equation (3) can be transformed to:

$$\begin{aligned} & \log \left(\det(\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H) \right) \\ & - \log \left(\det \left(\mathbf{I} + (\mathbf{I} + \mathbf{H}_{ea} \mathbf{Q}'_s \mathbf{H}_{ea}^H)^{-1} (\mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H) \right) \right) \end{aligned} \quad (36)$$

To assess the influence of different channel gain ratios between legitimate users and the eavesdroppers, we fix the legitimate users' channel gain and change the eavesdroppers'. The above equation (36) can be further transformed to

$$\begin{aligned} & \log(\det(\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H)) \\ & - \log(\det(\mathbf{I} + ((\mathbf{H}_{ea} \mathbf{H}_{ea}^H)^{-1} + \mathbf{Q}'_s)^{-1} \mathbf{Q}_s)) \end{aligned} \quad (37)$$

In the high-SNR regime, $E_s \rightarrow \infty$, according to (28), $\mathbf{Q}_s, \mathbf{Q}'_s \rightarrow \infty$, the term $(\mathbf{H}_{ea} \mathbf{H}_{ea}^H)^{-1}$ then can be omitted and the result is the following expression

$$\log(\det(\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H)) - \log(\det(\mathbf{I} + (\mathbf{Q}'_s)^{-1} \mathbf{Q}_s)), \quad (38)$$

Considering artificial noise, $(\mathbf{Q}'_s)^{-1} \mathbf{Q}_s = \rho / (1 - \rho) \mathbf{I}$. When ρ is fixed, then $\log(\det(\mathbf{I} + (\mathbf{Q}'_s)^{-1} \mathbf{Q}_s))$ would be a constant. From (38), the secrecy rate will increase even when the eavesdroppers have better statistical channel knowledge than the legitimate users.

VI. SIMULATION RESULTS

A system with $N_t = 4$ transmit antennas and $T = 2$ users as well as $K = 1, 2$ eavesdroppers is considered. Each user or eavesdropper is equipped with $N_r = 2$ and $N_k = 2$ receive antennas. $m = \frac{\sigma_{ea}^2}{\sigma_{ba}^2}$ represents the gain ratio between the main and wire-tap channel.




Fig. 4. BER performance with precoding techniques in $4 \times 4 \times 2$ MU-MIMO broadcast channel, $m = 0.5$

$$C_s = \max_{\mathbf{Q}_s \geq 0, \text{Tr}(\mathbf{Q}_s) = E_s} \log \left(\det \left((\mathbf{I} + \mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H)^{-1} (\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H) \right) \right) \quad (24)$$

$$C_s = \max_{\mathbf{Q}_s \geq 0, \text{Tr}(\mathbf{Q}_s) = E_s} \log \left(\det \left(\Gamma_{ba}(\mathbf{P}) \Phi_1(\mathbf{P}, \mathbf{Q}_s)^{-1} \Phi_2(\mathbf{P}, \mathbf{Q}_s) \right) \right) \quad (25)$$

$$\Phi_1(\mathbf{P}, \mathbf{Q}_s) = (\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} (\mathbf{I} + \mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H) \quad (26)$$

$$\Phi_2(\mathbf{P}, \mathbf{Q}_s) = (\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} (\mathbf{I} + \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H) \quad (27)$$

$$\begin{aligned} SA &= E \left[\Phi_1(\mathbf{P}, \mathbf{Q}_s)^{-1} \Phi_2(\mathbf{P}, \mathbf{Q}_s) \right] \\ &= E \left[\Phi_3(\mathbf{P}, \mathbf{Q}_s)^{-1} \left((\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} + (\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} \mathbf{H}_{ba} \mathbf{Q}_s \mathbf{H}_{ba}^H \right) \right] \end{aligned} \quad (31)$$

$$\Phi_3(\mathbf{P}, \mathbf{Q}_s) = (\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} + (\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} \mathbf{H}_{ea} \mathbf{Q}_s \mathbf{H}_{ea}^H \quad (32)$$

$$\begin{aligned} SA &= E \left[\left((\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} + \mathbf{E}_s \right)^{-1} \left((\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} + \mathbf{E}_s \right) \right] \\ &= E \left[\left((\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} + \mathbf{E}_s + \mathbf{I} \right)^{-1} \left((\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H)^{-1} - (\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} \right) \right] \end{aligned} \quad (33)$$

$$C_{sec}^{E_s \rightarrow \infty} = \log \left(\det \left((\mathbf{H}_{ea} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ea}^H)^{-1} (\mathbf{H}_{ba} \mathbf{P} \mathbf{P}^H \mathbf{H}_{ba}^H) \right) \right) \quad (34)$$





Fig. 5. Secrecy rate performance with precoding techniques in $4 \times 4 \times 4$ MU-MIMO broadcast channel

Fig. 6. Secrecy rate change with different artificial noise power ratio



B. Imperfect Channel State Information

In the simulations, the channel errors are modeled as a complex random Gaussian noise matrix \mathbf{E} following the distribution $\mathcal{CN}(0, \sigma_e^2)$. Then, the imperfect channel matrix \mathbf{H}^e is defined as

$$\mathbf{H}^e = \mathbf{H} + \mathbf{E} \quad (39)$$

We assume the channels of the legitimate users are perfect and the eavesdropper will have imperfect CSI.




Fig. 7. Secrecy rate with precoding techniques $4 \times 4 \times 4$ MU-MIMO broadcast channel with imperfect CSI

A. Perfect Channel State Information

In Fig. 4 the proposed LR-SO-THP+S-GMI algorithm has the best BER performance. In Fig. ??, in the scenario where $T > K$ the secrecy rate of the proposed algorithms have around 5 bits/Hz higher rate than the other precoding techniques. When $T = K$, Fig. 8(a) shows that the proposed algorithms achieve a higher secrecy rate than the other techniques at low SNRs. And the secrecy rate will converge to a constant which will depend on the gain ratio between the main and the wire-tap channels m .




Fig. 8. Secrecy rate with precoding techniques $4 \times 4 \times 2$ MU-MIMO broadcast channel with imperfect CSI, AN and $m = 2$

In Fig. 8(b), the secrecy rate performance is evaluated in the imperfect CSI scenario [53], [11], [54]. Compared with the secrecy rate performance in Fig. 8(a), the secrecy rate will suffer a huge decrease in the imperfect CSI scenario. When $T = K$, Fig. 8(b) shows that the secrecy rate at low SNR is degraded and the secrecy rate requires very high SNR to converge to a constant. It is worth noting that the proposed SO-THP+S-GMI has the best secrecy rate performance amongst the studied precoding techniques.

C. Imperfect Channel State Information With Artificial Noise

In Fig. 8(c) AN is added and the total transmit power E_s is the same as before. Fig. 8(d) shows the secrecy rate with the change of the transmit signal power ratio to the artificial noise. According to the secrecy performance of Fig. 8(d), 40% of the transmit power E_s is used to generate AN.

VII. CONCLUSION

Precoding techniques are widely used in the downlink of MU-MIMO wireless networks to achieve good BER performance. They also contribute to the improvement of the secrecy rate in physical layer. Among all the studied non-linear precoding techniques, the proposed SO-THP+S-GMI algorithm requires the lowest computational complexity which results in a significant improvement on the efficiency. The BER and the secrecy rate performances of the SO-THP+S-GMI algorithm are also superior to the existing linear and non-linear algorithms considered.

REFERENCES

- [1] S. Soni, H. Agrawal, and M. Sharma, "Analysis and comparison between aes and des cryptographic algorithm," *International Journal of Engineering and Innovative Technology (IJEIT)*, vol. 2, no. 3, December 2012.
- [2] C. Shannon, "Communication theory and secrecy systems," *Bell Telephone Laboratories*, 1949.
- [3] A. D. Wyner, "The wire-tap channel," *Bell Syst. Techn. J.*, vol. 54, no. 8, p. 1385–1357, October 1975.
- [4] I. Csiszar and J. K. orner, "Broadcast channels with condential messages," *IEEE Transcations on Information Theory*, vol. 24, no. 3, p. 339–348, May 1978.
- [5] S. Leung-Yan-Cheong and M. Hellman, "The gaussian wire-tap channel," *IEEE Transactions on Information Theory*, vol. 24, no. 4, pp. 451–456, July 1978.
- [6] F. Oggier and B. Hassibi, "The secrecy capacity of the mimo wiretap channel," *IEEE International Symposium on Information Theory*, pp. 524–528, July 2008.
- [7] S. Goel and R. Negi, "Guaranteeing secrecy using artificial noise," *IEEE Transactions on Wireless Communications*, vol. 7, no. 6, pp. 2180–2189, June 2008.
- [8] A. Mukherjee and A. Swindlehurst, "Jamming games in the mimo wiretap channel with an active eavesdropper," *IEEE Transactions on Signal Processing*, vol. 61, no. 1, pp. 82–91, Jan 2013.
- [9] X. Lu and R. C. de Lamare, "Opportunistic relay and jammer cooperation techniques for physical-layer security in buffer-aided relay networks," in *2015 International Symposium on Wireless Communication Systems (ISWCS)*. IEEE, 2015, pp. 691–695.
- [10] M. Costa, "Writing on dirty paper," *IEEE Transactions on Information Theory*, vol. 29, no. 3, pp. 439–441, May 1983.
- [11] T. Peng and R. C. de Lamare, "Adaptive buffer-aided distributed space-time coding for cooperative wireless networks," *IEEE Transactions on Communications*, vol. 64, no. 5, pp. 1888–1900, 2016.
- [12] K. Zu, R. C. de Lamare, and M. Haardt, "Generalized design of low-complexity block diagonalization type precoding algorithms for multiuser mimo systems," *IEEE Transactions on Communications*, vol. 61, no. 10, pp. 4232–4242, November 2013.
- [13] K. Zu and R. C. de Lamare, "Low-complexity lattice reduction-aided regularized block diagonalization for mu-mimo systems," *IEEE Communications Letters*, vol. 16, no. 6, pp. 925–928, June 2012.
- [14] M. Tomlinson, "New automatic equaliser employing modulo arithmetic," *Electronics Letters*, vol. 7, pp. 138–139, 1971.
- [15] C. T. Healy and R. C. de Lamare, "Design of ldpc codes based on multipath emd strategies for progressive edge growth," *IEEE Transactions on Communications*, vol. 64, no. 8, pp. 3208–3219, 2016.
- [16] K. Zu, R. C. de Lamare, and M. Haardt, "Multi-branch tomlinson-harashima precoding design for mu-mimo systems: Theory and algorithms," *IEEE Transactions on Communications*, vol. 62, no. 3, pp. 939–951, March 2014.
- [17] Y. Cai, R. C. de Lamare, L.-L. Yang, and M. Zhao, "Robust mmse precoding based on switched relaying and side information for multiuser mimo relay systems," *IEEE Transactions on Vehicular Technology*, vol. 64, no. 12, pp. 5677–5687, 2015.
- [18] R. C. de Lamare and R. Sampaio-Neto, "Minimum mean-squared error iterative successive parallel arbitrated decision feedback detectors for ds-cdma systems," *IEEE Transactions on Communications*, vol. 56, no. 5, pp. 778–789, 2008.
- [19] R. de Lamare, "Adaptive and iterative multi-branch mmse decision feedback detection algorithms for multi-antenna systems," *IEEE Transactions on Wireless Communications*, vol. 12, no. 10, pp. 5294–5308, 2013.
- [20] J. Gu and R. C. de Lamare, "Joint interference cancellation and relay selection algorithms based on greedy techniques for cooperative ds-cdma systems," *EURASIP Journal on Wireless Communications and Networking*, vol. 2016, no. 1, pp. 1–19, 2016.
- [21] Y. Cai, R. C. de Lamare, B. Champagne, B. Qin, and M. Zhao, "Adaptive reduced-rank receive processing based on minimum symbol-error-rate criterion for large-scale multiple-antenna systems," *IEEE Transactions on Communications*, vol. 63, no. 11, pp. 4185–4201, 2015.
- [22] L. Arevalo, R. de Lamare, and R. Sampaio-Neto, "Variable list detection for multiuser mimo systems," *IEEE Transactions on Vehicular Technology*, 2016.
- [23] V. Stankovic and M. Haardt, "Generalized design of multi-user mimo precoding matrices," *IEEE Transactions on Wireless Communications*, vol. 7, no. 3, pp. 953–961, March 2008.
- [24] Y. Cai, D. L. Ruyet, R. C. de Lamare, and D. Roviras, "Linear precoding based on switched relaying processing for multiuser mimo relay systems," *IEEE 12th International Workshop, Signal Processing Advances in Wireless Communications (SPAWC)*, pp. 351–355, June 2011.
- [25] G. Geraci, M. Egan, J. Yuan, A. Razi, and I. B. Collings, "Secrecy sum-rates for multi-user mimo regularized channel inversion precoding," *IEEE Transactions on Communications*, vol. 60, no. 11, pp. 3472–3482, November 2012.
- [26] M. Payaro, A. Perez-Neira, and M. Lagunas, "Achievable rates for generalized spatial tomlinson-harashima precoding in mimo systems," *IEEE 60th Vehicular Technology Conference*, vol. 4, pp. 2462–2466, 2004.
- [27] M. Mazrouei-Sebdani and W. Krzymien, "Vector perturbation precoding for network mimo: Sum rate, fair user scheduling, and impact of backhaul delay," *IEEE Transactions on Vehicular Technology*, vol. 61, no. 9, pp. 3946–3957.
- [28] P. Lin, S. Lai, and S. Lin, "On secrecy rate of the generalized artificial-noise assisted secure beamforming for wiretap channels," *IEEE Journal on Selected Areas in Communications*, vol. 31, no. 9, September 2013.
- [29] A. Chorti and H. Poor, "Achievable secrecy rates in physical layer secure systems with a helping interferer," *Computing, Networking and Communications (ICNC)*, pp. 18–22, Feb 2012.
- [30] H. Yao and W. Wornell, "Lattice-reduction-aided detectors for mimo communication systems," *Global Telecommunications Conference*, vol. 1, pp. 424–428, November 2002.
- [31] M. Taherzadeh, A. Mobasher, and A. Khandani, "Lll reduction achieves the receive diversity in mimo decoding," *IEEE Transactions on Information Theory*, vol. 53, no. 12, pp. 4801–4805, December 2007.
- [32] R. C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank processing based on joint and iterative interpolation, decimation, and filtering," *IEEE Transactions on Signal Processing*, vol. 57, no. 7, pp. 2503–2514, July 2009.
- [33] R. Fa, R. C. de Lamare, and L. Wang, "Reduced-rank stap schemes for airborne radar based on switched joint interpolation, decimation and filtering algorithm," *IEEE Transactions on Signal Processing*, vol. 58, no. 8, pp. 4182–4194, August 2010.
- [34] Z. Yang, R. de Lamare, and X. Li, "L1-regularized stap algorithms with a generalized sidelobe canceler architecture for airborne radar," *Signal*

Processing, *IEEE Transactions on*, vol. 60, no. 2, pp. 674–686, Feb 2012.

- [35] S. Song and W. Chen, “MMSE based greedy eigenmode selection for AF MIMO relay channels,” *IEEE Globecom*, Anaheim, CA, Dec. 2012.
- [36] R. C. de Lamare, R. Sampaio-Neto, and M. Haardt, “Blind adaptive constrained constant-modulus reduced-rank interference suppression algorithms based on interpolation and switched decimation,” *IEEE Transactions on Signal Processing*, vol. 59, no. 2, pp. 681–695, Feb 2011.
- [37] V. Stankovic and M. Haardt, “Successive optimization tomlinson-harashima precoding (so thp) for multi-user mimo systems,” *IEEE International Conference, Proceedings. (ICASSP '05)*, vol. 3, pp. 1117 – 1120, March 2005.
- [38] R. C. de Lamare and R. C. de Lamare, “Adaptive reduced-rank mmse filtering with interpolated fir filters and adaptive interpolators,” *IEEE Signal Processing Letters*, vol. 12, no. 3, March 2005.
- [39] W. Chen, L. Dai, K. B. Letaief, and Z. Cao, “A unified cross-layer framework for resource allocation in cooperative networks,” *IEEE Trans. Wireless Commun.*, vol. 7, no. 8, pp. 3000–3012, Aug. 2008.
- [40] R. Meng, R. C. de Lamare, and V. H. Nascimento, “Sparsity-aware affine projection adaptive algorithms for system identification,” in *Proc. Sensor Signal Processing for Defence Conference*, London, UK, 2011.
- [41] Z. Yang, R. de Lamare, and X. Li, “Sparsity-aware space-time adaptive processing algorithms with l1-norm regularisation for airborne radar,” *Signal Processing, IET*, vol. 6, no. 5, pp. 413–423, July 2012.
- [42] R. C. de Lamare and R. C. de Lamare, “Sparsity-aware adaptive algorithms based on alternating optimization and shrinkage,” *IEEE Signal Processing Letters*, vol. 21, no. 2, pp. 225–229, January 2014.
- [43] R. C. de Lamare and R. Sampaio-Neto, “Reduced-rank adaptive filtering based on joint iterative optimization of adaptive filters,” *IEEE Signal Process. Lett.*, vol. 14, no. 12, pp. 980–983, December 2007.
- [44] —, “Reduced-rank space-time adaptive interference suppression with joint iterative least squares algorithms for spread-spectrum systems,” *IEEE Transactions Vehicular Technology*, vol. 59, no. 3, pp. 1217–1228, March 2010.
- [45] —, “Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems,” *IEEE Transactions on Vehicular Technology*, vol. 60, no. 6, pp. 2482–2494, July 2011.
- [46] S. Li, R. C. de Lamare, and R. Fa, “Reduced-rank linear interference suppression for ds-ss systems based on switched approximations of adaptive basis functions,” *IEEE Transactions on Vehicular Technology*, vol. 60, no. 2, pp. 485–497, Feb 2011.
- [47] M. L. Honig and J. S. Goldstein, “Adaptive reduced-rank interference suppression based on the multistage wiener filter,” *IEEE Transactions on Communications*, vol. 50, no. 6, June 2002.
- [48] R. C. de Lamare, M. Haardt, and R. Sampaio-Neto, “Blind adaptive constrained reduced-rank parameter estimation based on constant modulus design for cdma interference suppression,” *IEEE Transactions on Signal Processing*, vol. 56, no. 6, June 2008.
- [49] H. Ruan and R. de Lamare, “Robust adaptive beamforming using a low-complexity shrinkage-based mismatch estimation algorithm,” *Signal Processing Letters, IEEE*, vol. 21, no. 1, pp. 60–64, Jan 2014.
- [50] F. Dietrich, P. Breun, and W. Utschick, “Robust tomlinsonharashima precoding for the wireless broadcast channel,” *IEEE Transactions on Signal Processing*, vol. 55, no. 2, pp. 631 – 644, Feb 2007.
- [51] S. Hakjia, L. Sang-Rim, and L. Inkyu, “Generalized channel inversion methods for multiuser mimo systems,” *IEEE Transactions on Communications*, vol. 57, no. 11, pp. 3489 – 3499, November 2009.
- [52] M. Huang, S. Zhou, and J. Wang, “Analysis of tomlinson-harashima precoding in multiuser mimo systems with imperfect channel state information,” *IEEE Transactions on Vehicular Technology*, vol. 57, no. 5, pp. 2856 – 2867, September 2008.
- [53] L. Landau, R. C. de Lamare, and M. Haardt, “Robust adaptive beamforming algorithms using the constrained constant modulus criterion,” *IET Signal Processing*, vol. 8, no. 5, pp. 447–457, 2014.
- [54] H. Ruan and R. C. de Lamare, “Robust adaptive beamforming using a low-complexity shrinkage-based mismatch estimation algorithm,” *IEEE Signal Processing Letters*, vol. 21, no. 1, pp. 60–64, 2014.
- [3] C. Shannon, “Communication theory of secrecy systems,” *Bell System Technical Journal*, vol. 28, no. 4, pp. 656715, Oct 1949.
- [4] A. D. Wyner, “The wire-tap channel,” *Bell System Technical Journal*, vol. 54, no. 8, pp. 13551387, 1975.
- [5] I. Csiszar and J. Korner, “Broadcast channels with confidential messages,” *IEEE Trans. Inform. Theory*, vol. 24, no. 3, pp. 339348, May 1978.
- [6] F. Oggier and B. Hassibi, “The secrecy capacity of the mimo wiretap channel,” *IEEE Trans. Inform. Theory*, vol. 57, no. 8, pp. 49614972, Aug 2011.
- [7] T. Liu and S. Shamai, “A note on the secrecy capacity of the multipleantenna wiretap channel,” *IEEE Trans. Inform. Theory*, vol. 55, no. 6, pp. 25472553, June 2009.
- [8] S. Goel and R. Negi, “Guaranteeing secrecy using artificial noise,” *IEEE Trans. Wireless Commun.*, vol. 7, no. 6, pp. 21802189, June 2008.
- [9] J. Zhang and M. Gursay, “Collaborative relay beamforming for secrecy,” in *IEEE International Conference on Communications (ICC)*, May 2010, pp. 15.
- [10] Y. Oohama, “Capacity theorems for relay channels with confidential messages,” in *IEEE International Symposium on Inform. Theory (ISIT)*, June 2007, pp. 926930.
- [11] A. Mukherjee, S. Fakoorian, J. Huang, and A. Swindlehurst, “Principles of physical layer security in multiuser wireless networks: A survey,” *IEEE Communications Surveys Tutorials*, vol. 16, no. 3, pp. 15501573, August 2014.
- [12] N. Zlatanov and R. Schober, “Buffer-aided relaying with adaptive link selection-fixed and mixed rate transmission,” *IEEE Trans. Inform. Theory*, vol. 59, no. 5, pp. 28162840, May 2013.
- [13] G. Chen, Z. Tian, Y. Gong, Z. Chen, and J. Chambers, “Max-ratio relay selection in secure buffer-aided cooperative wireless networks,” *IEEE Trans. Inform. Forensics and Security*, vol. 9, no. 4, pp. 719729, April 2014.
- [14] J. Huang and A. Swindlehurst, “Wireless physical layer security enhancement with buffer-aided relaying,” in *2013 Asilomar Conference on Signals, Systems and Computers*, Nov 2013, pp. 15601564.
- [15] K. Zu and R. de Lamare, “Low-complexity lattice reduction-aided regularized block diagonalization for mu-mimo systems,” *IEEE Communications Letters*, vol. 16, no. 6, pp. 925928, June 2012.
- [16] K. Zu, R. de Lamare, and M. Haardt, “Generalized design of low-complexity block diagonalization type precoding algorithms for multiuser mimo systems,” *IEEE Trans. Communications*, vol. 61, no. 10, pp. 42324242, October 2013.
- [17] K. Zu, R. de Lamare, and M. Haardt, “Multi-branch tomlinson-harashima precoding design for mu-mimo systems: Theory and algorithms,” *IEEE Trans. Communications*, vol. 62, no. 3, pp. 939951, March 2014.
- [18] X. Lu, K. Zu, and R. C. de Lamare, “Lattice-reduction aided successive optimization tomlinson-harashima precoding strategies for physical-layer security in wireless networks,” in *Sensor Signal Processing for Defence (SSPD)*, 2014, Sept 2014, pp. 15.
- [19] X. Lu and R. C. Lamare, “Buffer-aided relay selection for physical-layer security in wireless networks,” in *Proceedings of 19th International ITG Workshop on Smart Antennas (WSA)*, March 2015, pp. 15.
- [20] J. H. Lee and W. Choi, “Multiuser diversity for secrecy communications using opportunistic jammer selection: Secure dof and jammer scaling law,” *IEEE Trans. Signal Processing*, vol. 62, no. 4, pp. 828839, Feb 2014.
- [21] J. Chen, R. Zhang, L. Song, Z. Han, and B. Jiao, “Joint relay and jammer selection for secure two-way relay networks,” *IEEE Trans. Inform. Forensics and Security*, vol. 7, no. 1, pp. 310320, Feb 2012.
- [22] R. Aggarwal, C. E. Koksal, and P. Schniter, “On the design of large scale wireless systems,” *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 215–225, Feb. 2013.
- [23] W. Zhang, H. Ren, C. Pan, M. Chen, R. C. de Lamare, B. Du and J. Dai, “Large-Scale Antenna Systems With UL/DL Hardware Mismatch: Achievable Rates Analysis and Calibration”, *IEEE Trans. Commun.*, vol.63, no.4, pp. 1216-1229, April 2015.
- [24] C. Shepard, H. Yu, N. Anand, L. E. Li, T. L. Marzetta, R. Yang, and L. Zhong, Argos: Practical many-antenna base stations, in *ACM Int. Conf. Mobile Computing and Networking (MobiCom)*, Istanbul, Turkey, Aug. 2012.
- [25] X. Gao, F. Tufvesson, O. Edfors, and F. Rusek, Measured propagation characteristics for very-large MIMO at 2.6 GHz, in *Proc. of the 46th Annual Asilomar Conference on Signals, Systems, and Computers*, Pacific Grove, California, USA, Nov. 2012.

REFERENCES

- [1] T. L. Marzetta, Noncooperative cellular wireless with unlimited numbers of base station antennas, *IEEE Trans. Wireless Commun.*, vol. 9, no. 11, pp. 35903600, Nov. 2010.
- [2] R. C. de Lamare, “Massive MIMO Systems: Signal Processing Challenges and Future Trends”, *URSI Radio Science Bulletin*, 2013.

- [26] H. Q. Ngo, E. G. Larsson, and T. L. Marzetta, "Energy and spectral efficiency of very large multiuser MIMO systems", *IEEE Trans. Commun.*, vol. 61, no. 4, pp. 1436-1449, Apr. 2013.
- [27] H. Yang and T. L. Marzetta, "Performance of conjugate and zero-forcing beamforming in large-scale antenna systems", *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 1721-179, Feb. 2013.
- [28] K. Vardhan, S. Mohammed, A. Chockalingam and B. Rajan, "A low-complexity detector for large MIMO systems and multicarrier CDMA systems", *IEEE J. Sel. Commun.*, vol. 26, no. 3, pp. 473-485, Apr. 2008.
- [29] P. Li and R. D. Murch, "Multiple Output Selection-LAS Algorithm in Large MIMO Systems", *IEEE Commun. Lett.*, vol. 14, no. 5, pp. 399-401, May 2010.
- [30] J. W. Choi, A. C. Singer, J. Lee, N. I. Cho, "Improved linear soft-input soft-output detection via soft feedback successive interference cancellation", *IEEE Trans. Commun.*, vol. 58, no. 3, pp. 986-996, March 2010.
- [31] P. Li, R. C. de Lamare and R. Fa, "Multiple Feedback Successive Interference Cancellation Detection for Multiuser MIMO Systems", *IEEE Transactions on Wireless Communications*, vol. 10, no. 8, pp. 2434 - 2439, August 2011.
- [32] R.C. de Lamare, R. Sampaio-Neto, "Minimum mean-squared error iterative successive parallel arbitrated decision feedback detectors for DS-CDMA systems", *IEEE Trans. Commun.*, vol. 56, no. 5, May 2008, pp. 778-789.
- [33] R.C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems", *IEEE Trans. Veh. Technol.*, vol. 60, no. 6, pp. 2482-2494, July 2011.
- [34] R. C. de Lamare, "Adaptive and Iterative Multi-Branch MMSE Decision Feedback Detection Algorithms for Multi-Antenna Systems", *IEEE Trans. Wireless Commun.*, vol. 14, no. 10, October 2013.
- [35] T. Schenk, *RF Imperfections in High-rate Wireless Systems: Impact and Digital Compensation*, 1st ed. Springer, Feb. 2008.
- [36] S. Buzzi, M. Lops, and S. Sardellitti, "Widely linear reception strategies for layered space-time wireless communications", *IEEE Trans. Sig. Proc.*, vol. 54, no. 6, pp. 2252-2262, Jun. 2006.
- [37] P. Chevalier and A. Blin, "Widely linear MVDR beamformers for the reception of an unknown signal corrupted by noncircular interferences", *IEEE Trans. Sig. Proc.*, vol. 55, no. 11, pp. 5323-5336, Nov. 2007.
- [38] P. Chevalier and F. Dupuy, "Widely Linear Alamouti Receiver for the Reception of Real-Valued Constellations Corrupted by Interferences-The Alamouti-SAIC/MAIC Concept", *IEEE Trans. Sig. Proc.*, Vol. 59, No. 7, July 2011.
- [39] A. Hakkariainen, J. Werner, K. R. Dandekar and M. Valkama, "Widely-linear beamforming and RF impairment suppression in massive antenna arrays," *Journal of Communications and Networks*, vol.15, no.4, pp.383,397, Aug. 2013.
- [40] X. Wang and H. V. Poor, "Iterative (turbo) soft interference cancellation and decoding for coded CDMA," *IEEE Trans. Commun.*, vol. 47, pp. 1046-1061, July 1999.
- [41] R. C. de Lamare, "Massive MIMO Systems: Signal Processing Challenges and Future Trends", *Radio Science Bulletin*, December 2013.
- [42] W. Zhang, H. Ren, C. Pan, M. Chen, R. C. de Lamare, B. Du and J. Dai, "Large-Scale Antenna Systems With UL/DL Hardware Mismatch: Achievable Rates Analysis and Calibration", *IEEE Trans. Commun.*, vol.63, no.4, pp. 1216-1229, April 2015.
- [43] M. Costa, "Writing on dirty paper," *IEEE Trans. Inform. Theory*, vol. 29, no. 3, pp. 439-441, May 1983.
- [44] R. C. de Lamare and A. Alcaim, "Strategies to improve the performance of very low bit rate speech coders and application to a 1.2 kb/s codec" *IEE Proceedings- Vision, image and signal processing*, vol. 152, no. 1, February, 2005.
- [45] P. Clarke and R. C. de Lamare, "Joint Transmit Diversity Optimization and Relay Selection for Multi-Relay Cooperative MIMO Systems Using Discrete Stochastic Algorithms," *IEEE Communications Letters*, vol.15, no.10, pp.1035-1037, October 2011.
- [46] P. Clarke and R. C. de Lamare, "Transmit Diversity and Relay Selection Algorithms for Multirelay Cooperative MIMO Systems" *IEEE Transactions on Vehicular Technology*, vol.61, no. 3, pp. 1084-1098, October 2011.
- [47] Y. Cai, R. C. de Lamare, and R. Fa, "Switched Interleaving Techniques with Limited Feedback for Interference Mitigation in DS-CDMA Systems," *IEEE Transactions on Communications*, vol.59, no.7, pp.1946-1956, July 2011.
- [48] Y. Cai, R. C. de Lamare, D. Le Ruyet, "Transmit Processing Techniques Based on Switched Interleaving and Limited Feedback for Interference Mitigation in Multiantenna MC-CDMA Systems," *IEEE Transactions on Vehicular Technology*, vol.60, no.4, pp.1559-1570, May 2011.
- [49] T. Wang, R. C. de Lamare, and P. D. Mitchell, "Low-Complexity Set-Membership Channel Estimation for Cooperative Wireless Sensor Networks," *IEEE Transactions on Vehicular Technology*, vol.60, no.6, pp.2594-2607, July 2011.
- [50] T. Wang, R. C. de Lamare and A. Schmeink, "Joint linear receiver design and power allocation using alternating optimization algorithms for wireless sensor networks," *IEEE Trans. on Vehi. Tech.*, vol. 61, pp. 4129-4141, 2012.
- [51] R. C. de Lamare, "Joint iterative power allocation and linear interference suppression algorithms for cooperative DS-CDMA networks", *IET Communications*, vol. 6, no. 13, 2012, pp. 1930-1942.
- [52] T. Peng, R. C. de Lamare and A. Schmeink, "Adaptive Distributed Space-Time Coding Based on Adjustable Code Matrices for Cooperative MIMO Relaying Systems", *IEEE Transactions on Communications*, vol. 61, no. 7, July 2013.
- [53] K. Zu, R. C. de Lamare, "Low-Complexity Lattice Reduction-Aided Regularized Block Diagonalization for MU-MIMO Systems", *IEEE Communications Letters*, Vol. 16, No. 6, June 2012, pp. 925-928.
- [54] K. Zu, R. C. de Lamare, "Low-Complexity Lattice Reduction-Aided Regularized Block Diagonalization for MU-MIMO Systems", *IEEE Communications Letters*, Vol. 16, No. 6, June 2012.
- [55] K. Zu, R. C. de Lamare and M. Haardt, "Generalized design of low-complexity block diagonalization type precoding algorithms for multiuser MIMO systems", *IEEE Trans. Communications*, 2013.
- [56] M. Tomlinson, "New automatic equaliser employing modulo arithmetic," *Electronic Letters*, vol. 7, Mar. 1971.
- [57] C. T. Healy and R. C. de Lamare, "Decoder-optimised progressive edge growth algorithms for the design of LDPC codes with low error floors", *IEEE Communications Letters*, vol. 16, no. 6, June 2012, pp. 889-892.
- [58] A. G. D. Uchoa, C. T. Healy, R. C. de Lamare, R. D. Souza, "LDPC codes based on progressive edge growth techniques for block fading channels", *Proc. 8th International Symposium on Wireless Communication Systems (ISWCS)*, 2011, pp. 392-396.
- [59] A. G. D. Uchoa, C. T. Healy, R. C. de Lamare, R. D. Souza, "Generalised Quasi-Cyclic LDPC codes based on progressive edge growth techniques for block fading channels", *Proc. International Symposium Wireless Communication Systems (ISWCS)*, 2012, pp. 974-978.
- [60] A. G. D. Uchoa, C. T. Healy, R. C. de Lamare, R. D. Souza, "Design of LDPC Codes Based on Progressive Edge Growth Techniques for Block Fading Channels", *IEEE Communications Letters*, vol. 15, no. 11, November 2011, pp. 1221-1223.
- [61] H. Harashima and H. Miyakawa, "Matched-transmission technique for channels with intersymbol interference," *IEEE Trans. Commun.*, vol. 20, Aug. 1972.
- [62] K. Zu, R. C. de Lamare and M. Haardt, "Multi-branch tomlinson-harashima precoding for single-user MIMO systems," in *Smart Antennas (WSA)*, 2012 International ITG Workshop on , vol., no., pp.36-40, 7-8 March 2012.
- [63] K. Zu, R. C. de Lamare and M. Haardt, "Multi-Branch Tomlinson-Harashima Precoding Design for MU-MIMO Systems: Theory and Algorithms," *IEEE Transactions on Communications*, vol.62, no.3, pp.939,951, March 2014.
- [64] L. Zhang, Y. Cai, R. C. de Lamare and M. Zhao, "Robust Multibranch TomlinsonHarashima Precoding Design in Amplify-and-Forward MIMO Relay Systems," *IEEE Transactions on Communications*, vol.62, no.10, pp.3476,3490, Oct. 2014.
- [65] B. Hochwald, C. Peel and A. Swindlehurst, "A vector-perturbation technique for near capacity multiantenna multiuser communication - Part II: Perturbation," *IEEE Trans. Commun.*, vol. 53, no. 3, Mar. 2005.
- [66] C. B. Chae, S. Shim and R. W. Heath, "Block diagonalized vector perturbation for multiuser MIMO systems," *IEEE Trans. Wireless Commun.*, vol. 7, no. 11, pp. 4051 - 4057, Nov. 2008.
- [67] R. C. de Lamare, R. Sampaio-Neto, "Adaptive MBER decision feedback multiuser receivers in frequency selective fading channels", *IEEE Communications Letters*, vol. 7, no. 2, Feb. 2003, pp. 73 - 75.
- [68] A. Rontogiannis, V. Kekatos, and K. Berberidis, "A Square-Root Adaptive V-BLAST Algorithm for Fast Time-Varying MIMO Channels," *IEEE Signal Processing Letters*, Vol. 13, No. 5, pp. 265-268, May 2006.
- [69] R. C. de Lamare, R. Sampaio-Neto, A. Hjørungnes, "Joint iterative interference cancellation and parameter estimation for CDMA systems", *IEEE Communications Letters*, vol. 11, no. 12, December 2007, pp. 916 - 918.

- [70] Y. Cai and R. C. de Lamare, "Adaptive Space-Time Decision Feedback Detectors with Multiple Feedback Cancellation", *IEEE Transactions on Vehicular Technology*, vol. 58, no. 8, October 2009, pp. 4129 - 4140.
- [71] J. W. Choi, A. C. Singer, J. Lee, N. I. Cho, "Improved linear soft-input soft-output detection via soft feedback successive interference cancellation," *IEEE Trans. Commun.*, vol.58, no.3, pp.986-996, March 2010.
- [72] R. C. de Lamare and R. Sampaio-Neto, "Blind adaptive MIMO receivers for space-time block-coded DS-CDMA systems in multipath channels using the constant modulus criterion," *IEEE Transactions on Communications*, vol.58, no.1, pp.21-27, January 2010.
- [73] R. Fa, R. C. de Lamare, "Multi-Branch Successive Interference Cancellation for MIMO Spatial Multiplexing Systems", *IET Communications*, vol. 5, no. 4, pp. 484 - 494, March 2011.
- [74] R.C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems," *IEEE Trans. Veh. Technol.*, vol. 60, no. 6, pp. 2482-2494, July 2011.
- [75] P. Li, R. C. de Lamare and R. Fa, "Multiple Feedback Successive Interference Cancellation Detection for Multiuser MIMO Systems," *IEEE Transactions on Wireless Communications*, vol. 10, no. 8, pp. 2434 - 2439, August 2011.
- [76] R.C. de Lamare, R. Sampaio-Neto, "Minimum mean-squared error iterative successive parallel arbitrated decision feedback detectors for DS-CDMA systems," *IEEE Trans. Commun.*, vol. 56, no. 5, May 2008, pp. 778-789.
- [77] R.C. de Lamare, R. Sampaio-Neto, "Minimum mean-squared error iterative successive parallel arbitrated decision feedback detectors for DS-CDMA systems," *IEEE Trans. Commun.*, vol. 56, no. 5, May 2008.
- [78] R.C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems," *IEEE Trans. Veh. Technol.*, vol. 60, no. 6, pp. 2482-2494, July 2011.
- [79] P. Li, R. C. de Lamare and J. Liu, "Adaptive Decision Feedback Detection with Parallel Interference Cancellation and Constellation Constraints for Multiuser MIMO systems", *IET Communications*, vol.7, 2012, pp. 538-547.
- [80] J. Liu, R. C. de Lamare, "Low-Latency Reweighted Belief Propagation Decoding for LDPC Codes," *IEEE Communications Letters*, vol. 16, no. 10, pp. 1660-1663, October 2012.
- [81] P. Li and R. C. de Lamare, Distributed Iterative Detection With Reduced Message Passing for Networked MIMO Cellular Systems, *IEEE Transactions on Vehicular Technology*, vol.63, no.6, pp. 2947-2954, July 2014.
- [82] A. G. D. Uchoa, C. T. Healy and R. C. de Lamare, "Iterative Detection and Decoding Algorithms For MIMO Systems in Block-Fading Channels Using LDPC Codes," *IEEE Transactions on Vehicular Technology*, 2015.
- [83] R. C. de Lamare, "Adaptive and Iterative Multi-Branch MMSE Decision Feedback Detection Algorithms for Multi-Antenna Systems", *IEEE Trans. Wireless Commun.*, vol. 14, no. 10, October 2013.
- [84] L. L. Scharf and D. W. Tufts, "Rank reduction for modeling stationary signals," *IEEE Transactions on Acoustics, Speech and Signal Processing*, vol. ASSP-35, pp. 350-355, March 1987.
- [85] A. M. Haimovich and Y. Bar-Ness, "An eigenanalysis interference canceler," *IEEE Trans. on Signal Processing*, vol. 39, pp. 76-84, Jan. 1991.
- [86] D. A. Pados and S. N. Batalama, "Joint space-time auxiliary vector filtering for DS/CDMA systems with antenna arrays" *IEEE Transactions on Communications*, vol. 47, no. 9, pp. 1406 - 1415, 1999.
- [87] J. S. Goldstein, I. S. Reed and L. L. Scharf "A multistage representation of the Wiener filter based on orthogonal projections" *IEEE Transactions on Information Theory*, vol. 44, no. 7, 1998.
- [88] Y. Hua, M. Nikpour and P. Stoica, "Optimal reduced rank estimation and filtering," *IEEE Transactions on Signal Processing*, pp. 457-469, Vol. 49, No. 3, March 2001.
- [89] M. L. Honig and J. S. Goldstein, "Adaptive reduced-rank interference suppression based on the multistage Wiener filter," *IEEE Transactions on Communications*, vol. 50, no. 6, June 2002.
- [90] E. L. Santos and M. D. Zoltowski, "On Low Rank MVDR Beamforming using the Conjugate Gradient Algorithm", *Proc. IEEE International Conference on Acoustics, Speech and Signal Processing*, 2004.
- [91] Q. Haoli and S.N. Batalama, "Data record-based criteria for the selection of an auxiliary vector estimator of the MMSE/MVDR filter", *IEEE Transactions on Communications*, vol. 51, no. 10, Oct. 2003, pp. 1700 - 1708.
- [92] R. C. de Lamare and R. Sampaio-Neto, "Reduced-Rank Adaptive Filtering Based on Joint Iterative Optimization of Adaptive Filters", *IEEE Signal Processing Letters*, Vol. 14, no. 12, December 2007.
- [93] Z. Xu and M.K. Tsatsanis, "Blind adaptive algorithms for minimum variance CDMA receivers," *IEEE Trans. Communications*, vol. 49, No. 1, January 2001.
- [94] R. C. de Lamare and R. Sampaio-Neto, "Low-Complexity Variable Step-Size Mechanisms for Stochastic Gradient Algorithms in Minimum Variance CDMA Receivers", *IEEE Trans. Signal Processing*, vol. 54, pp. 2302 - 2317, June 2006.
- [95] C. Xu, G. Feng and K. S. Kwak, "A Modified Constrained Constant Modulus Approach to Blind Adaptive Multiuser Detection," *IEEE Trans. Communications*, vol. 49, No. 9, 2001.
- [96] Z. Xu and P. Liu, "Code-Constrained Blind Detection of CDMA Signals in Multipath Channels," *IEEE Sig. Proc. Letters*, vol. 9, No. 12, December 2002.
- [97] R. C. de Lamare and R. Sampaio Neto, "Blind Adaptive Code-Constrained Constant Modulus Algorithms for CDMA Interference Suppression in Multipath Channels", *IEEE Communications Letters*, vol 9, no. 4, April, 2005.
- [98] L. Landau, R. C. de Lamare and M. Haardt, "Robust adaptive beamforming algorithms using the constrained constant modulus criterion," *IET Signal Processing*, vol.8, no.5, pp.447-457, July 2014.
- [99] R. C. de Lamare, "Adaptive Reduced-Rank LCMV Beamforming Algorithms Based on Joint Iterative Optimisation of Filters", *Electronics Letters*, vol. 44, no. 9, 2008.
- [100] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank Processing Based on Joint and Iterative Interpolation, Decimation and Filtering", *IEEE Transactions on Signal Processing*, vol. 57, no. 7, July 2009, pp. 2503 - 2514.
- [101] R. C. de Lamare and Raimundo Sampaio-Neto, "Reduced-rank Interference Suppression for DS-CDMA based on Interpolated FIR Filters", *IEEE Communications Letters*, vol. 9, no. 3, March 2005.
- [102] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank MMSE Filtering with Interpolated FIR Filters and Adaptive Interpolators", *IEEE Signal Processing Letters*, vol. 12, no. 3, March, 2005.
- [103] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Interference Suppression for DS-CDMA Systems based on Interpolated FIR Filters with Adaptive Interpolators in Multipath Channels", *IEEE Trans. Vehicular Technology*, Vol. 56, no. 6, September 2007.
- [104] R. C. de Lamare, "Adaptive Reduced-Rank LCMV Beamforming Algorithms Based on Joint Iterative Optimisation of Filters," *Electronics Letters*, 2008.
- [105] R. C. de Lamare and R. Sampaio-Neto, "Reduced-rank adaptive filtering based on joint iterative optimization of adaptive filters", *IEEE Signal Process. Lett.*, vol. 14, no. 12, pp. 980-983, Dec. 2007.
- [106] R. C. de Lamare, M. Haardt, and R. Sampaio-Neto, "Blind Adaptive Constrained Reduced-Rank Parameter Estimation based on Constant Modulus Design for CDMA Interference Suppression", *IEEE Transactions on Signal Processing*, June 2008.
- [107] M. Yukawa, R. C. de Lamare and R. Sampaio-Neto, "Efficient Acoustic Echo Cancellation With Reduced-Rank Adaptive Filtering Based on Selective Decimation and Adaptive Interpolation," *IEEE Transactions on Audio, Speech, and Language Processing*, vol.16, no. 4, pp. 696-710, May 2008.
- [108] R. C. de Lamare and R. Sampaio-Neto, "Reduced-rank space-time adaptive interference suppression with joint iterative least squares algorithms for spread-spectrum systems," *IEEE Trans. Vehi. Technol.*, vol. 59, no. 3, pp. 1217-1228, Mar. 2010.
- [109] R. C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems," *IEEE Trans. Vehi. Technol.*, vol. 60, no. 6, pp. 2482-2494, Jul. 2011.
- [110] R. C. de Lamare, L. Wang, and R. Fa, "Adaptive reduced-rank LCMV beamforming algorithms based on joint iterative optimization of filters: Design and analysis," *Signal Processing*, vol. 90, no. 2, pp. 640-652, Feb. 2010.
- [111] R. Fa, R. C. de Lamare, and L. Wang, "Reduced-Rank STAP Schemes for Airborne Radar Based on Switched Joint Interpolation, Decimation and Filtering Algorithm," *IEEE Transactions on Signal Processing*, vol.58, no.8, Aug. 2010, pp.4182-4194.
- [112] L. Wang and R. C. de Lamare, "Low-Complexity Adaptive Step Size Constrained Constant Modulus SG Algorithms for Blind Adaptive Beamforming", *Signal Processing*, vol. 89, no. 12, December 2009, pp. 2503-2513.
- [113] L. Wang and R. C. de Lamare, "Adaptive Constrained Constant Modulus Algorithm Based on Auxiliary Vector Filtering for Beamforming,"

- IEEE Transactions on Signal Processing, vol. 58, no. 10, pp. 5408-5413, Oct. 2010.
- [114] L. Wang, R. C. de Lamare, M. Yukawa, "Adaptive Reduced-Rank Constrained Constant Modulus Algorithms Based on Joint Iterative Optimization of Filters for Beamforming," *IEEE Transactions on Signal Processing*, vol.58, no.6, June 2010, pp.2983-2997.
- [115] L. Wang, R. C. de Lamare and M. Yukawa, "Adaptive reduced-rank constrained constant modulus algorithms based on joint iterative optimization of filters for beamforming", *IEEE Transactions on Signal Processing*, vol.58, no. 6, pp. 2983-2997, June 2010.
- [116] L. Wang and R. C. de Lamare, "Adaptive constrained constant modulus algorithm based on auxiliary vector filtering for beamforming", *IEEE Transactions on Signal Processing*, vol. 58, no. 10, pp. 5408-5413, October 2010.
- [117] R. Fa and R. C. de Lamare, "Reduced-Rank STAP Algorithms using Joint Iterative Optimization of Filters," *IEEE Transactions on Aerospace and Electronic Systems*, vol.47, no.3, pp.1668-1684, July 2011.
- [118] Z. Yang, R. C. de Lamare and X. Li, "L1-Regularized STAP Algorithms With a Generalized Sidelobe Canceler Architecture for Airborne Radar," *IEEE Transactions on Signal Processing*, vol.60, no.2, pp.674-686, Feb. 2012.
- [119] Z. Yang, R. C. de Lamare and X. Li, "Sparsity-aware spacetime adaptive processing algorithms with L1-norm regularisation for airborne radar", *IET signal processing*, vol. 6, no. 5, pp. 413-423, 2012.
- [120] Neto, F.G.A.; Nascimento, V.H.; Zakharov, Y.V.; de Lamare, R.C., "Adaptive re-weighting homotopy for sparse beamforming," in *Signal Processing Conference (EUSIPCO)*, 2014 Proceedings of the 22nd European , vol., no., pp.1287-1291, 1-5 Sept. 2014
- [121] Almeida Neto, F.G.; de Lamare, R.C.; Nascimento, V.H.; Zakharov, Y.V., "Adaptive reweighting homotopy algorithms applied to beamforming," *IEEE Transactions on Aerospace and Electronic Systems*, vol.51, no.3, pp.1902-1915, July 2015.
- [122] L. Wang, R. C. de Lamare and M. Haardt, "Direction finding algorithms based on joint iterative subspace optimization," *IEEE Transactions on Aerospace and Electronic Systems*, vol.50, no.4, pp.2541-2553, October 2014.
- [123] S. D. Somasundaram, N. H. Parsons, P. Li and R. C. de Lamare, "Reduced-dimension robust capon beamforming using Krylov-subspace techniques," *IEEE Transactions on Aerospace and Electronic Systems*, vol.51, no.1, pp.270-289, January 2015.
- [124] S. Xu and R.C de Lamare, , *Distributed conjugate gradient strategies for distributed estimation over sensor networks*, *Sensor Signal Processing for Defense SSPD*, September 2012.
- [125] S. Xu, R. C. de Lamare, H. V. Poor, "Distributed Estimation Over Sensor Networks Based on Distributed Conjugate Gradient Strategies", *IET Signal Processing*, 2016 (to appear).
- [126] S. Xu, R. C. de Lamare and H. V. Poor, *Distributed Compressed Estimation Based on Compressive Sensing*, *IEEE Signal Processing letters*, vol. 22, no. 9, September 2014.
- [127] S. Xu, R. C. de Lamare and H. V. Poor, "Distributed reduced-rank estimation based on joint iterative optimization in sensor networks," in *Proceedings of the 22nd European Signal Processing Conference (EUSIPCO)*, pp.2360-2364, 1-5, Sept. 2014
- [128] S. Xu, R. C. de Lamare and H. V. Poor, "Adaptive link selection strategies for distributed estimation in diffusion wireless networks," in *Proc. IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, , vol., no., pp.5402-5405, 26-31 May 2013.
- [129] S. Xu, R. C. de Lamare and H. V. Poor, "Dynamic topology adaptation for distributed estimation in smart grids," in *Computational Advances in Multi-Sensor Adaptive Processing (CAMSAP)*, 2013 IEEE 5th International Workshop on , vol., no., pp.420-423, 15-18 Dec. 2013.
- [130] S. Xu, R. C. de Lamare and H. V. Poor, "Adaptive Link Selection Algorithms for Distributed Estimation", *EURASIP Journal on Advances in Signal Processing*, 2015.
- [131] N. Song, R. C. de Lamare, M. Haardt, and M. Wolf, "Adaptive Widely Linear Reduced-Rank Interference Suppression based on the Multi-Stage Wiener Filter," *IEEE Transactions on Signal Processing*, vol. 60, no. 8, 2012.
- [132] N. Song, W. U. Alokozai, R. C. de Lamare and M. Haardt, "Adaptive Widely Linear Reduced-Rank Beamforming Based on Joint Iterative Optimization," *IEEE Signal Processing Letters*, vol.21, no.3, pp. 265-269, March 2014.
- [133] R.C. de Lamare, R. Sampaio-Neto and M. Haardt, "Blind Adaptive Constrained Constant-Modulus Reduced-Rank Interference Suppression Algorithms Based on Interpolation and Switched Decimation," *IEEE Trans. on Signal Processing*, vol.59, no.2, pp.681-695, Feb. 2011.
- [134] Y. Cai, R. C. de Lamare, "Adaptive Linear Minimum BER Reduced-Rank Interference Suppression Algorithms Based on Joint and Iterative Optimization of Filters," *IEEE Communications Letters*, vol.17, no.4, pp.633-636, April 2013.
- [135] R. C. de Lamare and R. Sampaio-Neto, "Sparsity-Aware Adaptive Algorithms Based on Alternating Optimization and Shrinkage," *IEEE Signal Processing Letters*, vol.21, no.2, pp.225,229, Feb. 2014.